

A-320HVA Handheld Vehicle Adapter

Overview

The A-320HVA Handheld Vehicle Adapter is the ultimate solution for vehicle communications. Now you can use the same handheld radio mounted or dismounted. The A-320HVA brings the proven technology of the A-320* amplifier into the vehicle. It is designed specifically for "jerk-and-run" scenarios, and compatibility with widely fielded radios from Thales and others. The A-320HVA features a universal pocket that accepts up to 16 radios (including variants).

The A-320HVA can be used in tactical or non-standard vehicles as it is capable of operating from any 11-36 volt DC power supply. Additionally, the power supply allows the user to attach an amplified speaker such as the MRC-67A to provide an audio interface.

*A-320HVA compatible with A-320V1, A-320V2-A and A-320V3 only.

Features

- Universal charging pocket supports 16 radios, including variants:
 - Thales AN/PRC-148 MBITR
 - Thales AN/PRC-148 JEM
 - AN/PRC-152 and all variants

Follow Us Online:

in

 S^+

Tube

Ø

- ITT Soldier Radio



www.ultralifecorporation.com/commsys 800-332-5000 | orders@ulbi.com





A-320HVA Technical Specifications

Part No.	A-320HVA
Size (H x W x D - inches)	6 x 7.5 x 11.5
Weight	< 5lbs (without radio & amplifier)
Input Voltage	11-36 VDC (215 W max, 120 W with cigarette lighter adapter)
Reliability	9,550 hours
MIL-STD-810G Qualifications - Environmental	Temperature Shock Vibration Altitude Humidity Rain Salt Fog Sand & Dust
Operating Temperature	-31° to +60° C
Input Connector	MIL-26482 Series II
Speaker Power Connector	MIL-26482 Series II
Switch	3-position toggle On/Off/Blackout
LED Indicators	3-color
Finish	Black
Accessories Optional	MRC-67A amplified speaker Cigarette lighter adapter



www.ultralifecorporation.com/commsys 800-332-5000 | orders@ulbi.com



©2014 Ultralife Corporation • www.ultralifecorp.com • all specifications subject to change without notice The information contained herein is for reference only and does not constitute a warranty of performance • ULCS-9000-0014_B 5/30/14